

The following pages were
extracted from the:

*COMPAQ SERVICE
QUICK REFERENCE GUIDE*

DP386/25e

COMPAQ DESKPRO 386/25e

BOARD COMPATIBILITY LIST

<u>Product</u>	<u>Assy No.</u>	<u>Spare Part No.</u>	<u>Page</u>
SYSTEM BOARDS			
386/25e System	001427	122078-001	133
MEMORY BOARDS			
4MB Memory Module	000758/000993/ 001166-001/002	113226-001	X
1MB Memory Module	000762/000981/ 001076/001151-001 001256/001259	113225-001	X
1MB 32-Bit Memory	000960	112518-001	X
4MB 32-Bit Memory	000963	112517-001	X
CONTROLLER BOARDS			
Tape Adapter	000774	113259-001	A-3
ESDI External 300/600	001091	115839-001	A-3
15 MHz ESDI Cntrl	001628	121667-001	A-4
ESDI/Diskette Cntrl	001472	115374-001	A-4
VIDEO BOARDS			
Advanced Graphics 1024	109958	114201-001	A-8
Advanced Graphics Memory	109959	114202-001	X
VGA Pass-Through	001430	114241-001	X
MISCELLANEOUS			
Serial/Parallel Interface	000570	106886-001	A-8
Serial/Parallel Interface	000990	106886-001	A-9
2400-Baud Int Modem	001070	112693-001	X

DP386/25e

COMPAQ DESKPRO 386/25e

FIXED DISK DRIVES

Drive Size	Drive Type	Inter-leave	Inte-grated	Min ROM	Spare Part No.	Controller Assy No.
40 MB*	43	1:1	Y	P.6	112526-001	N/A
40 MB	22	1:1	Y	P.6	112526-001	N/A
60 MB	55	1:1	Y	P.6	122079-001	N/A
84 MB	27	1:1	Y	P.6	112438-001	N/A
110 MB*	33	1:1	Y	P.6	112525-001	N/A
120 MB	50	1:1	Y	P.6	122080-001	N/A
210 MB	51	1:1	Y	P.6	124013-001	N/A
300 MB ¹	38	1:1	N	P.6	113219-001	001628
320 MB	28	1:1	N	P.6	115182-001	001628

* See page A-13 for single and dual fixed disk drive switch settings and configuration.

¹ Used in Fixed Disk Expansion Unit. Requires MS-DOS 3.3 or later

TAPE DRIVES

Drive Size	Spare Part No.	Tape Cartridge	Spare Part No.
40/60 MB	112524-001	40 MB (DC 2000)	108142-001
		60 MB	122086-001
80/120 MB	122087-001	80 MB	116966-001
		120 MB	116967-001
150/250 MB	115220-001	150 MB (DC 600 XTD)	113234-001
		250 MB	115298-001

DISKETTE DRIVES

Size	Spare Part No.
360 KB	112567-001
1.2 MB	112566-001
1.44 MB*	112565-001

*Requires MS-DOS Version 3.31 Revision A if installed as drive B, and MS-DOS Version 3.31 Revision B if installed as drive A.

DP386/25e

COMPAQ DESKPRO 386/25e

CABLE INFORMATION

Cable Function	Used With	Spare Part No.	
Diskette/Tape Signal	All Diskette Drives 40/60-MB Tape	113594-001	34 Pin
Mass Storage Power	All Diskette & Tape Drives	113596-001	
Mass Storage Power	40-, 60-, 84-, 110-, 120-, & 210-MB FDD Drive C	101741-001	6 In.
Mass Storage Power	40-, 60-, 84-, 110-, 120-, & 210-MB FDD Drive D	101741-004	15 In.
Mass Storage Power	320-MB FDD	115215-001	
Mass Storage Signal	320-MB FDD	100625-006 115197-001	20-Pin 34 Pin
Tape Signal	80-/120- & 150-/250-MB Tape Drives	113198-002	
FDD Signal	40-, 60-, 84-, 110-, 120-, & 210-MB FDD Drive C	113595-001	40 Pins
FDD Signal	40-, 60-, 84-, 110-, 120-, & 210-MB FDD Drive D	112528-001	40 Pins Y
External I/O	Expansion Unit	115810-001	
Telephone Cable	Modem	112666-001	
VGA Pass-Through	Adv Graphics	114229-001	

BOARD JUMPER/SWITCH SETTINGS

SYSTEM BOARD (001427)

Switch	Setting	Function
S1	ON*	Enable Integrated VGA
S1	OFF	Disable Integrated VGA
S2	ON*	Disable Power-On Password
S2	OFF	Enable Power-On Password

* Default

DP386/25e

COMPAQ DESKPRO 386/25e

PROCESSOR/COPROCESSOR LOCATIONS

<u>Processor (386-25)</u>	<u>Coprocessor (387-25)</u>
U139	U140
<u>Weitek 3167 Coprocessor (Spare Part No. 115517-001)</u>	
U140	

SYSTEM ROM INFORMATION

SYSTEM ROM LOCATIONS

U119 ODD
U141 EVEN

SYSTEM ROM REVISIONS (Spare Part No. 112694-001)

<u>Rev</u>	<u>PN on ODD ROM</u>	<u>PN on EVEN ROM</u>
P.6	122095-001	122096-001
R.2	122095-002	122096-002

POWER SUPPLY

Spare Part No. 112570-001

BATTERY/CLOCK MODULE

Spare Part No. 107872-001