

Numeric Code	Word Code	Result
0	OK	The command line was successfully processed.
1	CONNECT	The Carrier signal has been detected.
2	RING	The phone is ringing.
3	NO CARRIER	Carrier was not detected or was lost.
4	ERROR	There was an error in the command line.
5	CONNECT 1200	Carrier has been detected at 1200 bps.
6	NO DIAL TONE	No dial tone has been detected by the PC Modem.
7	BUSY	The PC Modem has detected a busy signal.
8	NO ANSWER	Called modem does not answer.

## Notes:

- \* V0 and V1 determine whether the modem returns numeric (V0) or verbal (V1) result codes.
- \* Q determines whether or not results are sent.
- \* The defaults for the V and Q commands are set by DIP switches on the modem board.
- \* The X command also relates to the result code. Depending on the selected value of this command, the result code that appears varies.

(dkh-07/28/93)