

# CONNECTOR

**CN1** : FDC connector  
**CN3** : IDE Primary connector  
**CN5** : GAME port connector  
**CN7** : Serial port A connector  
**J1** : IDE Secondary indicator

**CN2** : IDE Secondary connector  
**CN4** : Parallel port B connector  
**CN6** : Serial port B connector  
**CN8** : Parallel port A connector  
**J2** : IDE Primary indicator

# BASE ADDRESS

**COM 1** : 3F8-3FF Hex  
**COM 2** : 2F8-2FF Hex  
**COM 3** : 3E8-3EF Hex  
**COM 4** : 2E8-2EF Hex  
 Floppy Primary : 3F0-3F7 Hex  
 Floppy Secondary : 370-377 Hex  
 Hard Disk Primary : 1F0-1F7, 3F6, 3F7 Hex  
 Hard Disk Secondary : 170-177, 376, 377 Hex  
**LPT2** : 378 Hex  
**LPT3** : 278 Hex  
**LPT1** : 3BC Hex (can not use in EPP mode)

# JUMPER SETTING

## JP1 : Serial Address and IRQ Selection

<b>COM A selection</b> 		COM 1 (3F8)		COM 3 (3E8)
		COM 4 (2E8)		Disable
<b>COM B selection</b> 		COM 2 (2F8)		COM 3 (3E8)
		COM 4 (2E8)		Disable
<b>COM A IRQ selection</b>				
<b>COM B IRQ selection</b>				

### JP2: PRINTER DMA/DACK and IRQ Selection

<b>DMA for printer A,B</b>  30 29 28		DMA1 (printer A)		DMA3 (printer A)
		DMA1 (printer B)		DMA3 (printer B)
<b>DACK for printer A,B</b>  30 29 28		DACK1 (printer A)		DACK3 (printer A)
		DACK1 (printer B)		DACK3 (printer B)
<b>Printer A IRQ selection</b>  30 29 28 IRQ5 IRQ7 IRQ9 IRQ10 IRQ11 IRQ12		<b>Printer B IRQ selection</b>  30 29 28 IRQ5 IRQ7 IRQ9 IRQ10 IRQ11 IRQ12		

### JP3: PRINTER Address and Mode Selection

<b>Printer A address selection</b>  24 23 22		LPT 3 (278)		LPT 1 (38C)
		LPT 2 (378)		Disable
<b>Printer B address selection</b>  24 23 22		LPT 3 (278)		LPT 1 (38C)
		LPT 2 (378)		Disable
<b>Printer A Mode Selection</b>  24 23 22		SPP Mode		ECP Mode
		EPP Mode		EXT2FDD
<b>Printer B Mode selection</b>  24 23 22		SPP Mode		ECP Mode
		EPP Mode		EXT2FDD

### JP4: HDD /FDC Address Selection

<b>HDD selection</b>  15 14 13		HDD 1 Enable		HDD 1 Disable
		HDD 2 Enable		HDD 2 Disable
<b>FDC selection</b>  15 14 13		Enable		Disable
		Normal mode		A&B Change
		Primary		Secondary

