

SHORT FORM	LONG FORM	DESCRIPTION
0	OK	Command line executed without errors.
1	CONNECT	Connection established at 300 bps.
2	RING	Ring detected.
3	NO CARRIER	Carrier lost or never received.
4	ERROR	Error in command line.
5	CONNECT 1200	Connection established at 1200 bps.
6	NO DIAL TONE	No dial tone received.
7	BUSY	Busy signal detected.
8	NO ANSWER	5 sec. silence not det. for @ cmd.
9	CONNECT 600	Connection established at 600 bps.
10	CONNECT 2400	Connection established at 2400 bps.

Long form result codes are preceded and terminated by carriage return and line feed characters. Short form codes are terminated by a line feed.

(smm 07/28/93)